



DA-7X2 V1.05 Recovery Quick Card

Identify the route - then continue in the dedicated guide

STOP - choose one row only: Do not try these key combinations as alternatives. Use only the route assigned by the named guide or BTECH Support. If the expected screen does not appear, power off without writing.

Purpose	Power-on keys	Expected state	Primary guide
Main firmware update or directed retry	PTT + PF3/Alarm	Documented main-update indication	Firmware Update Guide
Radio initialization after main firmware	PTT + PF1	Initialize-radio confirmation	Firmware Update Guide
Normal NR-board update	PF3 + PF2	UPDATE MODE FOR LinkBoard	NR Board Update and Recovery Guide
NR/APRS null-data recovery	PF1 + PF3	Forced NR update state	NR Board Update and Recovery Guide

Before one controlled retry

- Confirm DA-7X2 model identity, battery charge, cable, COM port, and the exact guide route.
- For main firmware, keep the chosen Standard or NXDN triplet intact and select only its .spi member.
- For NR recovery, use only the supplied JL Bootloader and NR V112 .ufw file.
- Photograph the screen and record versions, filenames, percentage, and last successful step.

Stop after a repeated failure: Do not cycle through other modes or payloads. Send the evidence through the official BTECH Support channel. Do not post your serial number or codeplug publicly.